

SAMSUNG

GSM TELEPHONE

SGH-L810V

SERVICE *Manual*

GSM TELEPHONE



CONTENTS

1. Safety Precautions
2. Specification
3. Product Function
4. Array course control
5. Exploded View and Parts List
6. Main Electrical Parts List
7. Block Diagrams
8. PCB Diagrams
9. Flow Chart of Troubleshooting
10. Reference data
11. Disassembly and Assembly Instructions

**SAMSUNG
ELECTRONICS**



GSPN (Global Service Partner Network)

Country	Web Site
North America	service.samsungportal.com
Latin America	latin.samsungportal.com
CIS	cis.samsungportal.com
Europe	europe.samsungportal.com
China	china.samsungportal.com
Asia	asia.samsungportal.com
Mideast & Africa	mea.samsungportal.com

2. Specification

2-1. GSM General Specification


	EGSM 900	DCS 1800	PCS 1900	WCDMA2100
Freq. Band[MHz] Uplink/Downlink	880~915 925~960	1710~1785 1805~1880	1850~1910 1930~1990	1920~1980 2110~2170
ARFCN range	0~124 & 975~1023	512~885	512~810	UL:9612~9888 DL:10562~10838
Tx/Rx spacing	45MHz	95MHz	80MHz	190MHz
Mod. Bit rate/ Bit Period	270.833kbps 3.692us	270.833kbps 3.692us	270.833kbps 3.692us	3.84Mcps
Time Slot Period/Frame Period	576.9us 4.615ms	576.9us 4.615ms	576.9us 4.615ms	Frame length : 10ms Slot length: 0.667ms
Modulation	0.3GMSK	0.3GMSK	0.3GMSK	QPSK HQPSK
MS Power	33dBm~5dBm	30dBm~0dBm	30dBm~0dBm	24dBm~ -50dBm
Power Class	⁴ (max +33dBm)	¹ (max +30dBm)	¹ (max +30dBm)	³ (max +24dBm)
Sensitivity	-102dBm	-100dBm	-100dBm	-106.7dBm
TDMA Mux	8	8	8	NA
Cell Radius	35Km	2Km	2Km	2Km

2-2. GSM Tx Power Class

TX Power control level	GSM900	TX Power control level	DCS1800	TX Power control level	PCS1800
5	33±2 dBm	0	30±3 dBm	0	30±3 dBm
6	31±2 dBm	1	28±3 dBm	1	28±3 dBm
7	29±2 dBm	2	26±3 dBm	2	26±3 dBm
8	27±2 dBm	3	24±3 dBm	3	24±3 dBm
9	25±2 dBm	4	22±3 dBm	4	22±3 dBm
10	23±2 dBm	5	20±3 dBm	5	20±3 dBm
11	21±2 dBm	6	18±3 dBm	6	18±3 dBm
12	19±2 dBm	7	16±3 dBm	7	16±3 dBm
13	17±2 dBm	8	14±3 dBm	8	14±3 dBm
14	15±2 dBm	9	12±4 dBm	9	12±4 dBm
15	13±2 dBm	10	10±4 dBm	10	10±4 dBm
16	11±3 dBm	11	8±4dBm	11	8±4dBm
17	9±3dBm	12	6±4 dBm	12	6±4 dBm
18	7±3 dBm	13	4±4 dBm	13	4±4 dBm
19	5±3 dBm	14	2±5 dBm	14	2±5 dBm
		15	0±5 dBm	15	0±5 dBm

5. Exploded View and Parts List

5-1. Cellular phone Exploded View



5-2. Cellular phone Parts list

Design LOC		Discription	SEC CODE
QAN02		INTENNA-SGHL810V	GH42-01578A
QAN08		ASSY RUBBER-BATT CONTACT	GH98-08972A
QBA00		ASSY CASE-BATT	GH98-08202A
QBA01		INNER BATTERY PACK-880MAH , BL	GH43-02666A
QCA01		CAMERA MODULE-SGHL810V 3M/CIF	GH59-05738A
QCA02		KEY FPCB-SGHL810V CAMERA KEY	GH59-05740A
QCR04		SCREW-MACHINE	6001-001479
QCR05		SCREW-MACHINE	6001-001478
QCR05		SCREW-MACHINE	6001-001478
QFL01		ASSY CASE-SLIDE LOWER	GH98-08184A
QFR01		ASSY CASE-FRONT	GH98-08181A
QHI01		ASSY HINGE-MODULE	GH98-08183A
QMP01		PBA MAIN-SGHL810V	GH92-04564A
QPC01		FPC-SGHZV70 MAIN FPCB	GH41-02156A
QRF01		PMO COVER-RF	GH72-47510A
QSH04		IPR SHIELD-CAN REAR B	GH70-03501A
QSH05		IPR SHIELD-COVER REAR_A	GH70-03211A
QSH06		IPR SHIELD-CAN FRONT	GH70-03502A
QSP01		ASSY ETC-SGHL810V SPK/MOT	GH59-05743A
QVK01		KEY FPCB-SGHL810V VOLUME KEY	GH59-05739A
QLC01		LCD-MODULE SGHZV70	GH07-01287A
	QME02	DOME SHEET-SGHL810V NAVY	GH59-05744A
QFU01		ASSY CASE-SLIDE UPPER	GH98-08178A
	QKP02	ASSY KEYPAD-SUB	GH98-08204A
	QMW02	PMO WINDOW-MAIN	GH72-47514A
QRE01		ASSY CASE-REAR	GH98-08182A
	QCK01	PMO KEY-CAMERA	GH72-47516A
	QIF01	PMO COVER-IF	GH72-47513A
	QSD01	PMO COVER-SD	GH72-47512A
	QVO01	PMO KEY-VOLUME	GH72-47515A

7. Disassembly and Assembly Instructions


7-1. Disassembly

1



1) Unscrew the 6 points of the REAR.

2



1) Be care of the scratch.


1) Detach the REAR from slide ass'y.

3




1) Detach the FPCB connector by using the pincette.

4




1) Detach the volume key from the molding.
2) Detach the camera key from the molding.

5




- 1) Detach the mic from holder by using pincette.
- 2) Detach the PBA, pushing the rib to the left side.

6




- 1) Put the PBA upside down

7




- 1) Detach the electric tape by using pincette.
- 2) Detach the connector from the PBA.

8




- 1) Unscrew the 6 points on the LOWER.

9




1) Detach the electric tape by using pincette.

10




1) Take out the FPCB connector through the hole.
Be careful.
2) Detach the front from the Upper Ass'y.

11



1) Detach the 2 points on the LOWER bottom.

12



1) Detach the LOWER from the UPPER.

13



- 1) Detach the module from top side.
 - 2) Detach the LCD ass'y from the lower.
- Be careful.

14



- 1) The END.

7-2. Assembly

1




- 1) Attach the LCD ass'y to the LOWER.
- 2) Be careful of the bottom side rib.

2



- 1) Attach the LOWER to the UPPER.

3






- 2) Screw the 2 points on the LOWER bottom side.

4



- 1) Put in the FPCB connector through the hole.
Be careful of damage.

5 	6 
1) Attach the electric tape matching the shape. 2) Screw the 6 point.	1) Attach the non-elctric tape to the LOWER.
7 	8 
1) FPCB 커넥터를 결함한다. Attach the FPCB connector. 2) Attach the electric tape to the top of connector.	1) Turn upside down the PBA 2) Attach the FPCB connector. 3) Attach the key FPCB(volume key, camera key) to the molding.

9



1) Be careful of scratch.

1) Attach the REAR to the slide ass'y.


10




1) Screw down six points.
2) The END.


10. Flow Chart of Troubleshooting



10-1. Power On









10-2. Initial











10-3. Charging Part







10-4. Sim Part





10-5. Microphone Part








EARMIC PATH






10-6. Speaker Part








10-7. Receiver Part








10-8. LCD part








10-9. FM RADIO Part






10-10. GSM Receiver







RF TRANSCEIVER

10-11 GSM Transmitter








RF TRANSCEIVER






2G PAM






10-12. DCS Receiver







RF TRANSCEIVER

10-29




10-13. DCS Transmitter








RF TRANSCEIVER






2G PAM






10-14. PCS Receiver









RF TRANSCEIVER




10-15. PCS Transmitter










10-16. WCDMA Receiver









RF TRANSCEIVER






10-17. WCDMA Transmitter












10-18. Bluetooth Part





4. Array course control

4-1. Software Adjustments

1. JIG(GH80-03308A): Download, Trace, Calibration, etc



2. 0.4M Test cable(GH39-00886A): JIG to phone



3. 1.5M Test cable(GH39-00890A): JIG to phone



4.Travel Adaptor(GH44-01702A)



5.Data Link Cable(GH39-00922A): USB cable



6.Serial cable(LJ39-00013A) : PC to JIG



7. RF test cable(GH39-00397A): RF test



4-2. Software Downloading

4-2-1. Downloading Binary Files


- Four binary files for downloading L810V
 - amss_compressed.bin : Modem binary for communication function and user interface and various application
 - Rsrc_L810_Vodafone.rc1 : Files need for each application
 - Rsrc2_L810V(Low).rc2 : Power on/off animation
 - FactoryFs_L810_Vodafone.ffs : Default file system to be put into in initial production

4-2-2. Pre-requisite for Downloading


- Downloader Program ([MultiLoader V5.32.exe](#))
- SGH-L810V Mobile Phone
- USB Data Link Cable
- Binary files

4-2-3. S/W Downloader Program


1. Boot the L810V by pressing 'power ON' + 'star(*)' at the same time.
If you do properly, you can see the following message on Main LCD "Download"
2. Load the binary download program by executing the "**MultiLoader V5.32.exe**".
And the Check the **MSM6245/MSM6260**



3. Select the binary file what you want to download and drag all




4. Select the check box what you want to download.



* Up to eight ports are supported.

5. Now press the button 'DownLoad'.




6. When downloading is complete, UE reboot automatically.
 -If there is difference in FactoryFS.bin, UE will format file system automatically.

8. Block Diagrams

8-1. RF Block Diagram


SGH-L810V BLUETOOTH & RADIO BLOCK DIAGRAM



1. Main top



2. Main bottom



3. Product Function

Main Function

- Bluetooth Class 2
- Extended GSM 900MHz & DCS1800MHz & PCS1900MHz & WCDMA 2100MHz Quad Band
- Slide type
- Color LCD (2.2" QVGA 39.19×54.62×2.05t_max)
- Built-in 3 Mega pixel and CIF Camera
- Built-in MP3 Player
- GPRS Multi-slot Class 12
- Downloadable Game via JAVA
- Sending Photo & Video by MMS or E-Mail
- External Memory Card Socket (T-flash)
- 880mAh Battery

11. Reference data

11-1. Reference Abbreviate

AAC: Advanced Audio Coding.

AVC : Advanced Video Coding.

BER : Bit Error Rate

BPSK: Binary Phase Shift Keying

CA : Conditional Access

CDM : Code Division Multiplexing

C/I : Carrier to Interference

DMB : Digital Multimedia Broadcasting

EN : European Standard

ES : Elementary Stream

ETSI: European Telecommunications Standards Institute

MPEG: Moving Picture Experts Group

PN : Pseudo-random Noise

PS : Pilot Symbol

QPSK: Quadrature Phase Shift Keying

RS : Reed-Solomon

SI : Service Information

TDM : Time Division Multiplexing

TS : Transport Stream

1. Safety Precautions

1-1. Repair Precaution

- Repair in Shield Box, during detailed tuning.
Take specially care of tuning or test,
because specipicty of cellular phone is sensitive for surrounding interference(RF noise).
- Be careful to use a kind of magnetic object or tool,
because performance of parts is damaged by the influence of manetic force.
- Surely use a standard screwdriver when you disassemble this product,
otherwise screw will be worn away.
- Use a thicken twisted wire when you measure level.
A thicken twisted wire has low resistance, therefore error of measurement is few.
- Repair after separate Test Pack and Set because for short danger (for example an
overcurrent and furious flames of parts etc) when you repair board in condition of
connecting Test Pack and tuning on.
- Take specially care of soldering, because Land of PCB is small and weak in heat.
- Surely tune on/off while using AC power plug, because a repair of battery charger is
dangerous when tuning ON/OFF PBA and Connector after disassembling charger.
- Don't use as you pleases after change other material than replacement registered on SEC
System.
Otherwise engineer in charge isn't charged with problem that you don't keep this rules.

1-2. ESD(Electrostatically Sensitive Devices) Precaution

Several semiconductor may be damaged easily by static electricity. Such parts are called by ESD(Electrostatically Sensitive Devices), for example IC,BGA chip etc. Read Precaution below. You can prevent from ESD damage by static electricity.

- Remove static electricity remained your body before you touch semiconductor or parts with semiconductor. There are ways that you touch an earthed place or wear static electricity prevention string on wrist.
- Use earthed soldering steel when you connect or disconnect ESD.
- Use soldering removing tool to break static electricity. , otherwise ESD will be damaged by static electricity.
- Don't unpack until you set up ESD on product. Because most of ESD are packed by box and aluminum plate to have conductive power,they are prevented from static electricity.
- You must maintain electric contact between ESD and place due to be set up until ESD is connected completely to the proper place or a circuit board.

6. MAIN Electrical Parts List

SEC CODE	Design LOC	Discription
0403-001547	D600	DIODE-ZENER
0404-001172	D401	DIODE-SCHOTTKY
0406-001190	D501	DIODE-TVS
0406-001201	D601	DIODE-TVS
0406-001203	C102	DIODE-TVS
0406-001254	D605	DIODE-TVS
0406-001254	D606	DIODE-TVS
0406-001254	D607	DIODE-TVS
0406-001254	D608	DIODE-TVS
0406-001254	ZD300	DIODE-TVS
0406-001254	ZD504	DIODE-TVS
0406-001254	ZD505	DIODE-TVS
0406-001254	ZD600	DIODE-TVS
0406-001254	ZD601	DIODE-TVS
0406-001254	ZD603	DIODE-TVS
0406-001254	ZD605	DIODE-TVS
0406-001267	ZD501	DIODE-TVS
0406-001267	ZD506	DIODE-TVS
0406-001303	ZD502	DIODE-TVS
0406-001303	ZD503	DIODE-TVS
0406-001303	ZD606	DIODE-TVS
0406-001303	ZD607	DIODE-TVS
0406-001303	ZD608	DIODE-TVS
0406-001303	ZD609	DIODE-TVS
0406-001303	ZD610	DIODE-TVS
0406-001304	D602	DIODE-ARRAY
0406-001304	D603	DIODE-ARRAY
0406-001304	D604	DIODE-ARRAY
0407-001002	D400	DIODE-ARRAY
0504-000168	Q400	TR-DIGITAL
0504-001151	Q200	TR-DIGITAL
1001-001428	U305	IC-ANALOG MULTIPLEX
1001-001428	U404	IC-ANALOG MULTIPLEX
1001-001447	U504	IC-ANALOG MULTIPLEX
1009-001035	U303	IC-HALL EFFECT S/W
1009-001035	U304	IC-HALL EFFECT S/W
1108-000172	UME300	IC-MCP

6-1SEC CODE□Design LOC□Discription□□

SEC CODE	Design LOC	Discription
1201-002461	U201	IC-POWER AMP
1201-002671	U102	IC-POWER AMP
1201-002692	U500	IC-AUDIO AMP
1203-004776	U602	IC-POSI.FIXED REG
1203-004778	U400	IC-POWER SUPERVISOR
1203-004838	U402	IC-BATTERY
1205-003281	UCP300	IC-MODEM
1205-003341	U202	IC-TRANSCEIVER
1209-001712	U300	IC-SENSOR
1405-001082	V605	VARISTOR
1405-001133	V501	VARISTOR
1405-001133	V502	VARISTOR
1405-001167	V503	VARISTOR
1405-001167	V504	VARISTOR
1405-001167	V505	VARISTOR
1405-001167	V506	VARISTOR
1405-001167	V507	VARISTOR
1405-001167	V508	VARISTOR
2007-000138	R318	R-CHIP
2007-000138	R412	R-CHIP
2007-000138	R526	R-CHIP
2007-000138	R602	R-CHIP
2007-000140	R505	R-CHIP
2007-000140	R508	R-CHIP
2007-000140	R509	R-CHIP
2007-000140	R510	R-CHIP
2007-000144	R409	R-CHIP
2007-000148	R304	R-CHIP
2007-000148	R307	R-CHIP
2007-000148	R314	R-CHIP
2007-000148	R315	R-CHIP
2007-000148	R316	R-CHIP
2007-000148	R317	R-CHIP
2007-000148	R320	R-CHIP
2007-000148	R511	R-CHIP
2007-000148	R530	R-CHIP
2007-000148	R531	R-CHIP

SEC CODE	Design LOC	Discription
2007-000149	R200	R-CHIP
2007-000151	R529	R-CHIP
2007-000157	R410	R-CHIP
2007-000157	R518	R-CHIP
2007-000157	R519	R-CHIP
2007-000157	R520	R-CHIP
2007-000157	R521	R-CHIP
2007-000157	R522	R-CHIP
2007-000162	R413	R-CHIP
2007-000162	R415	R-CHIP
2007-000162	R501	R-CHIP
2007-000162	R516	R-CHIP
2007-000165	R411	R-CHIP
2007-000165	R414	R-CHIP
2007-000165	R419	R-CHIP
2007-000165	R517	R-CHIP
2007-000170	R300	R-CHIP
2007-000171	C601	R-CHIP
2007-000171	L100	R-CHIP
2007-000171	R103	R-CHIP
2007-000171	R104	R-CHIP
2007-000171	R105	R-CHIP
2007-000171	R107	R-CHIP
2007-000171	R115	R-CHIP
2007-000171	R512	R-CHIP
2007-000171	R513	R-CHIP
2007-000173	R321	R-CHIP
2007-000173	R504	R-CHIP
2007-000758	R322	R-CHIP
2007-000758	R323	R-CHIP
2007-001288	R109	R-CHIP
2007-001292	R112	R-CHIP
2007-001298	R108	R-CHIP
2007-001298	R207	R-CHIP
2007-001298	R211	R-CHIP
2007-001298	R301	R-CHIP
2007-001298	R406	R-CHIP

SEC CODE	Design LOC	Discription
2007-001307	R113	R-CHIP
2007-001307	R114	R-CHIP
2007-001319	R302	R-CHIP
2007-001319	R303	R-CHIP
2007-001319	R507	R-CHIP
2007-003010	R525	R-CHIP
2007-003010	R528	R-CHIP
2007-003030	R514	R-CHIP
2007-003030	R515	R-CHIP
2007-007009	R208	R-CHIP
2007-007014	R308	R-CHIP
2007-007014	R309	R-CHIP
2007-007014	R310	R-CHIP
2007-007014	R312	R-CHIP
2007-007014	R313	R-CHIP
2007-007014	R405	R-CHIP
2007-007014	R407	R-CHIP
2007-007014	R408	R-CHIP
2007-007133	R110	R-CHIP
2007-007133	R111	R-CHIP
2007-007193	R201	R-CHIP
2007-007306	R106	R-CHIP
2007-007306	R209	R-CHIP
2007-007306	R210	R-CHIP
2007-007306	R502	R-CHIP
2007-007306	R503	R-CHIP
2007-007316	R416	R-CHIP
2007-007317	R417	R-CHIP
2007-007317	R500	R-CHIP
2007-007317	R506	R-CHIP
2007-007318	R202	R-CHIP
2007-007318	R418	R-CHIP
2007-007468	R404	R-CHIP
2007-007586	R311	R-CHIP
2007-007766	R523	R-CHIP
2007-007766	R527	R-CHIP
2203-000138	C238	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-000233	C106	C-CER,CHIP
2203-000233	C203	C-CER,CHIP
2203-000233	C205	C-CER,CHIP
2203-000233	C209	C-CER,CHIP
2203-000233	C215	C-CER,CHIP
2203-000233	C229	C-CER,CHIP
2203-000233	C232	C-CER,CHIP
2203-000233	C239	C-CER,CHIP
2203-000233	C241	C-CER,CHIP
2203-000233	C429	C-CER,CHIP
2203-000233	C430	C-CER,CHIP
2203-000233	C433	C-CER,CHIP
2203-000233	C439	C-CER,CHIP
2203-000233	L115	C-CER,CHIP
2203-000254	C124	C-CER,CHIP
2203-000254	C127	C-CER,CHIP
2203-000254	C217	C-CER,CHIP
2203-000254	C226	C-CER,CHIP
2203-000254	C246	C-CER,CHIP
2203-000254	C305	C-CER,CHIP
2203-000254	C306	C-CER,CHIP
2203-000254	C308	C-CER,CHIP
2203-000254	C313	C-CER,CHIP
2203-000254	C314	C-CER,CHIP
2203-000254	C325	C-CER,CHIP
2203-000254	C327	C-CER,CHIP
2203-000278	C504	C-CER,CHIP
2203-000330	C207	C-CER,CHIP
2203-000330	C413	C-CER,CHIP
2203-000330	C428	C-CER,CHIP
2203-000359	C244	C-CER,CHIP
2203-000386	L208	C-CER,CHIP
2203-000425	C502	C-CER,CHIP
2203-000425	C510	C-CER,CHIP
2203-000438	C125	C-CER,CHIP
2203-000438	C234	C-CER,CHIP
2203-000438	C242	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-000438	C243	C-CER,CHIP
2203-000438	C253	C-CER,CHIP
2203-000438	C326	C-CER,CHIP
2203-000489	C337	C-CER,CHIP
2203-000627	C210	C-CER,CHIP
2203-000627	C220	C-CER,CHIP
2203-000627	C223	C-CER,CHIP
2203-000627	C224	C-CER,CHIP
2203-000627	C230	C-CER,CHIP
2203-000627	C235	C-CER,CHIP
2203-000627	C507	C-CER,CHIP
2203-000628	C214	C-CER,CHIP
2203-000628	C216	C-CER,CHIP
2203-000628	C219	C-CER,CHIP
2203-000628	C237	C-CER,CHIP
2203-000643	C208	C-CER,CHIP
2203-000679	C506	C-CER,CHIP
2203-000679	C541	C-CER,CHIP
2203-000812	C107	C-CER,CHIP
2203-000812	C116	C-CER,CHIP
2203-000812	C117	C-CER,CHIP
2203-000812	C118	C-CER,CHIP
2203-000812	C132	C-CER,CHIP
2203-000812	C222	C-CER,CHIP
2203-000812	C251	C-CER,CHIP
2203-000812	C255	C-CER,CHIP
2203-000812	C323	C-CER,CHIP
2203-000812	C332	C-CER,CHIP
2203-000812	C406	C-CER,CHIP
2203-000812	C431	C-CER,CHIP
2203-000812	C501	C-CER,CHIP
2203-000812	C505	C-CER,CHIP
2203-000812	C509	C-CER,CHIP
2203-000812	C527	C-CER,CHIP
2203-000812	C532	C-CER,CHIP
2203-000812	C537	C-CER,CHIP
2203-000812	C542	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-000812	C543	C-CER,CHIP
2203-000812	C544	C-CER,CHIP
2203-000995	C302	C-CER,CHIP
2203-000995	C602	C-CER,CHIP
2203-001153	C200	C-CER,CHIP
2203-001153	C201	C-CER,CHIP
2203-002668	C108	C-CER,CHIP
2203-002668	C112	C-CER,CHIP
2203-002668	C115	C-CER,CHIP
2203-002677	C122	C-CER,CHIP
2203-002709	C110	C-CER,CHIP
2203-002709	C131	C-CER,CHIP
2203-002709	C231	C-CER,CHIP
2203-002709	C340	C-CER,CHIP
2203-002709	C341	C-CER,CHIP
2203-002709	C342	C-CER,CHIP
2203-002709	C343	C-CER,CHIP
2203-002709	C346	C-CER,CHIP
2203-002709	C347	C-CER,CHIP
2203-002709	C437	C-CER,CHIP
2203-002709	C503	C-CER,CHIP
2203-002709	C508	C-CER,CHIP
2203-002709	C529	C-CER,CHIP
2203-002709	C535	C-CER,CHIP
2203-003054	C528	C-CER,CHIP
2203-003054	C531	C-CER,CHIP
2203-003054	C533	C-CER,CHIP
2203-003054	C539	C-CER,CHIP
2203-005050	C103	C-CER,CHIP
2203-005053	R100	C-CER,CHIP
2203-005288	C252	C-CER,CHIP
2203-005288	R102	C-CER,CHIP
2203-005382	C245	C-CER,CHIP
2203-005444	C221	C-CER,CHIP
2203-005444	C225	C-CER,CHIP
2203-005450	C119	C-CER,CHIP
2203-005480	C519	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-005480	C520	C-CER,CHIP
2203-005482	C104	C-CER,CHIP
2203-005482	C328	C-CER,CHIP
2203-005482	C329	C-CER,CHIP
2203-005482	C330	C-CER,CHIP
2203-005482	C331	C-CER,CHIP
2203-005482	C338	C-CER,CHIP
2203-005482	C405	C-CER,CHIP
2203-005482	C407	C-CER,CHIP
2203-005482	C408	C-CER,CHIP
2203-005482	C409	C-CER,CHIP
2203-005482	C411	C-CER,CHIP
2203-005571	C434	C-CER,CHIP
2203-005571	C435	C-CER,CHIP
2203-006048	C303	C-CER,CHIP
2203-006048	C304	C-CER,CHIP
2203-006048	C309	C-CER,CHIP
2203-006048	C315	C-CER,CHIP
2203-006048	C316	C-CER,CHIP
2203-006257	C603	C-CER,CHIP
2203-006260	C521	C-CER,CHIP
2203-006260	C522	C-CER,CHIP
2203-006324	C403	C-CER,CHIP
2203-006324	C438	C-CER,CHIP
2203-006348	C436	C-CER,CHIP
2203-006348	C443	C-CER,CHIP
2203-006399	C425	C-CER,CHIP
2203-006399	C440	C-CER,CHIP
2203-006474	C444	C-CER,CHIP
2203-006562	C105	C-CER,CHIP
2203-006562	C310	C-CER,CHIP
2203-006562	C311	C-CER,CHIP
2203-006562	C317	C-CER,CHIP
2203-006562	C321	C-CER,CHIP
2203-006562	C322	C-CER,CHIP
2203-006562	C412	C-CER,CHIP
2203-006562	C441	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-006562	C442	C-CER,CHIP
2203-006562	C517	C-CER,CHIP
2203-006562	C523	C-CER,CHIP
2203-006562	C524	C-CER,CHIP
2203-006562	C525	C-CER,CHIP
2203-006562	C534	C-CER,CHIP
2203-006562	C545	C-CER,CHIP
2203-006562	C600	C-CER,CHIP
2203-006562	C604	C-CER,CHIP
2203-006681	C202	C-CER,CHIP
2203-006681	C204	C-CER,CHIP
2203-006681	C206	C-CER,CHIP
2203-006681	C211	C-CER,CHIP
2203-006681	C212	C-CER,CHIP
2203-006681	C213	C-CER,CHIP
2203-006681	C218	C-CER,CHIP
2203-006681	C233	C-CER,CHIP
2203-006681	C236	C-CER,CHIP
2203-006681	C307	C-CER,CHIP
2203-006681	C324	C-CER,CHIP
2203-006681	C334	C-CER,CHIP
2203-006681	C335	C-CER,CHIP
2203-006681	C339	C-CER,CHIP
2203-006681	C344	C-CER,CHIP
2203-006681	C345	C-CER,CHIP
2203-006681	C404	C-CER,CHIP
2203-006824	C227	C-CER,CHIP
2203-006824	C228	C-CER,CHIP
2203-006824	C240	C-CER,CHIP
2203-006824	C301	C-CER,CHIP
2203-006824	C400	C-CER,CHIP
2203-006824	C401	C-CER,CHIP
2203-006824	C402	C-CER,CHIP
2203-006824	C415	C-CER,CHIP
2203-006824	C420	C-CER,CHIP
2203-006824	C421	C-CER,CHIP
2203-006824	C432	C-CER,CHIP

SEC CODE	Design LOC	Discription
2203-006838	C414	C-CER,CHIP
2203-006838	C416	C-CER,CHIP
2203-006838	C511	C-CER,CHIP
2203-006838	C514	C-CER,CHIP
2203-006841	C540	C-CER,CHIP
2203-006872	C318	C-CER,CHIP
2203-006872	C333	C-CER,CHIP
2203-006872	C417	C-CER,CHIP
2203-006872	C418	C-CER,CHIP
2203-006872	C419	C-CER,CHIP
2203-006872	C422	C-CER,CHIP
2203-006872	C423	C-CER,CHIP
2203-006872	C424	C-CER,CHIP
2203-006872	C426	C-CER,CHIP
2203-006872	C427	C-CER,CHIP
2203-006890	C300	C-CER,CHIP
2203-007195	C410	C-CER,CHIP
2404-001406	C606	C-TA,CHIP
2404-001474	TA500	C-TA,CHIP
2404-001496	TA100	C-TA,CHIP
2703-001180	L105	INDUCTOR-SMD
2703-001733	L203	INDUCTOR-SMD
2703-001733	L207	INDUCTOR-SMD
2703-001737	L206	INDUCTOR-SMD
2703-001750	L201	INDUCTOR-SMD
2703-002155	L103	INDUCTOR-SMD
2703-002207	L113	INDUCTOR-SMD
2703-002208	L102	INDUCTOR-SMD
2703-002208	L209	INDUCTOR-SMD
2703-002267	L109	INDUCTOR-SMD
2703-002267	L110	INDUCTOR-SMD
2703-002268	L204	INDUCTOR-SMD
2703-002281	L107	INDUCTOR-SMD
2703-002281	L108	INDUCTOR-SMD
2703-002309	L506	INDUCTOR-SMD
2703-002309	L507	INDUCTOR-SMD
2703-002309	L508	INDUCTOR-SMD

SEC CODE	Design LOC	Discription
2703-002367	L205	INDUCTOR-SMD
2703-002368	C250	INDUCTOR-SMD
2703-002369	L114	INDUCTOR-SMD
2703-002551	U603	INDUCTOR-SMD
2703-002551	U604	INDUCTOR-SMD
2703-002593	L104	INDUCTOR-SMD
2703-002593	L106	INDUCTOR-SMD
2703-002597	L200	INDUCTOR-SMD
2703-002608	L202	INDUCTOR-SMD
2703-002708	L112	INDUCTOR-SMD
2703-003205	L503	INDUCTOR-SMD
2703-003205	L504	INDUCTOR-SMD
2703-003205	L505	INDUCTOR-SMD
2703-003258	L400	INDUCTOR-SMD
2703-003258	L401	INDUCTOR-SMD
2703-003258	L402	INDUCTOR-SMD
2801-004339	OSC400	CRYSTAL-SMD
2809-001323	TCX100	OSCILLATOR-VCTCXO
2901-001409	F600	FILTER-EMI SMD
2901-001409	F603	FILTER-EMI SMD
2901-001409	F604	FILTER-EMI SMD
2901-001409	F605	FILTER-EMI SMD
2901-001422	F601	FILTER-EMI SMD
2901-001422	F602	FILTER-EMI SMD
2904-001703	F102	FILTER-SAW
2904-001769	F200	FILTER-SAW
2904-001789	F201	FILTER-SAW
2910-000024	F202	DUPLEXER-SAW
2911-000096	F101	DUPLEXER-FEM
3301-001342	L301	BEAD-SMD
3301-001342	L302	BEAD-SMD
3301-001421	L501	BEAD-SMD
3301-001421	L502	BEAD-SMD
3301-001792	L509	BEAD-SMD
3301-001792	L510	BEAD-SMD
3301-001792	L511	BEAD-SMD
3705-001358	RFS100	CONNECTOR-COAXIAL

SEC CODE	Design LOC	Discription
3709-001448	CD500	CONNECTOR-CARD EDGE
3709-001487	SIM500	CONNECTOR-CARD EDGE
3710-002523	IFC500	SOCKET-INTERFACE
3711-006278	HDC600	HEADER-BOARD TO BOARD
3711-006329	BTC600	HEADER-BATTERY
3711-006782	HDC601	HEADER-BOARD TO BOARD
4202-001453	BT_ANT100	ANTENNA-CHIP
4302-001180	BAT400	BATTERY-LI(2ND)
4709-001399	F203	COUPLER-DIRECTION
4709-001546	F100	BLUETOOTH MODULE
GH70-03349A	FPC600	IPR SHIELD-CAN CLIP
GH70-03349A	FPC601	IPR SHIELD-CAN CLIP
GH70-03349A	FPC602	IPR SHIELD-CAN CLIP
GH70-03349A	FPC603	IPR SHIELD-CAN CLIP
GH70-03349A	FPC604	IPR SHIELD-CAN CLIP
GH70-03349A	FPC605	IPR SHIELD-CAN CLIP
GH70-03349A	FPC606	IPR SHIELD-CAN CLIP
GH70-03349A	FPC607	IPR SHIELD-CAN CLIP
GH70-03349A	FPC608	IPR SHIELD-CAN CLIP
GH70-03349A	FPC609	IPR SHIELD-CAN CLIP
GH70-03349A	FPC610	IPR SHIELD-CAN CLIP
GH70-03519A	CONTACT600	IPR COVER-BATTERY CONTACT

Please consult the GSPN website (Samsung Portal) for the most recent version of the product's part list.